

Thin Client Models Cross Reference

Technical Specifications	Ino 9000 Series				Compact 9000 Series				Ultra 9000 Series				Atomino 9000 Series				
	XT9000-I	XT9200-I	XP9400-I	WE9700-I	WT9000-C	WT9100-C	XT9000-C	XT9200-C	XP9400-C	WE9700-C	WT9100-U	XT9000-U	XT9200-U	XP9400-U	WE9700-U	XT9050-A	XP9400-A
Processor/ Chipset	VIA Eden ULV 1GHz / VX855				VIA C7 1GHz / VIA VX800				VIA Eden ULV 1.6GHz / VIA VX800				Intel Atom N270 1.6GHz 845GSE				
Power supply	external 100/240VAC 50/60Hz, 12V 3A - 36W				external 100/240VAC 50/60Hz, 12VDC / 4A max				external 100/240VAC 50/60Hz, 12VDC / 4A max				external 100/240VAC 50/60Hz, 12VDC / 4A max				
Power consumption: on / stand-by	9W / 1.9W standard, 11W /1.9W con wifi				15W / 2.4W standard, 17W /2.4W with wifi				16W / 2.4W standard, 18W /2.4W with wifi				13W / 1.95W standard, 15W /1.95W with wifi				
Device dimension, weight	15,6(H) x 12,2(P) x 3,6(L) cm, 0,680 Kg				23,0(H) x 21,0(P) x 4,4(L) cm, 1,4Kg				23,0(H) x 21,0(P) x 5,7(L) cm, 1,7Kg				15,6(H) x 12,2(P) x 3,6(L) cm, 0,75 Kg				
Packaging dimension, weight	21,6(H) x 23,5(P) x 8,3(L) cm, 1,450 Kg				36,5(H) x 31,0(P) x 8,5(L) cm, 2,6Kg				36,5(H) x 31,0(P) x 8,5(L) cm, 2,8Kg				22,1(H) x 23,2(P) x 8,5(L) cm, 1,520 Kg				
Device certifications / Power Supply certification	CE, FCC Class B, UL / CE, FCC Class B, GS TUV,UL				CE, FCC Class B / CE, FCC Class B, GS TUV,UL				CE, FCC Class B / CE, FCC Class B, GS TUV,UL				CE, FCC Class B / CE, FCC Class B, GS TUV,UL				
Temperature range / humidity	0° ÷ 35° / 20% ÷ 80%				0° ÷ 35° / 20% ÷ 80%				0° ÷ 35° / 20% ÷ 80%				0° ÷ 35° / 20% ÷ 80%				
Security lock	kensington				kensington				kensington				kensington				
Display resolution with DDC, 4:3, 16:10 WIDE	1920 x 1440				1920 x 1440				1920 x 1440				1920 x 1440				
Colors	from 256 to 16,8 Millions				from 256 to 16,8 Millions				from 256 to 16,8 Millions				from 256 to 16,8 Millions				
Optical PS/2 mouse	included				included				included				included				
PS/2 Mouse and keyboard adapter	included				included				included				included				
DVI-I to VGA adapter	included				included				--				included				
Peripherals																	
USB external ports	2 USB 2.0 front + 2 USB 2.0 rear				2 USB 2.0 front + 2 USB 2.0 rear				2 USB 2.0 front + 2 USB 2.0 rear				2 USB 2.0 front + 2 USB 2.0 rear				
USB internal ports	2 USB 2.0 reserved for opt built-in wifi and Smart Card				2 USB 2.0 reserved for opt built-in wifi and Smart Card reader				2 USB 2.0 reserved for opt built-in wifi and Smart Card reader				1 USB 2.0 port reserved for opt. built-in wifi				
LAN Ethernet	10/100/1000 BaseT Ethernet RJ45				10/100/1000 BaseT Ethernet RJ45				10/100/1000 BaseT Ethernet RJ45				10/100/1000 BaseT Ethernet RJ45				
Monitor	1 DVI-I port with DVI-VGA adapter				1 DVI-I port with DVI-VGA adapter				1 DB15 VGA port, 1 DVI port				1 DVI-I port with DVI-VGA adapter				
PS/2 Mouse and Keyboard	1 PS/2 port, with PS/2 mouse + keyboard adapter				1 PS/2 port, with PS/2 mouse + keyboard adapter				1 PS/2 port, with PS/2 mouse + keyboard adapter				1 PS/2 port, with PS/2 mouse + keyb. adapter				
Serial port	--				1 COM1 port				1 COM1 port + optional COM2 port				--				
Parallel Port	With optional USB to Parallel cable adapter				With optional USB to Parallel cable adapter				1 LPT1 optional parallel port				With optional USB to Parallel cable adapter				
Audio In MIC / Audio Out Headphones	1 x 1/8 inch jack / 1 x 1/8 inch jack				1 x 1/8 inch jack / 1 x 1/8 inch jack				1 x 1/8 inch jack / 1 x 1/8 inch jack				1 x 1/8 inch jack / 1 x 1/8 inch jack				
Expansion slot	--				--				1 PCI expansion slot				--				
Buil-in 802.11b/g/n Wireless	Factory option with built-in antenna				Factory option with built-in antenna				Factory option with built-in antenna				Factory option with external antenna				
Built-in speaker	Built-in speaker 1 W				Built-in speaker 1 W				Built-in speaker 1 W				Built-in speaker 1 W				
Dual monitor native support	DVI and VGA with optional adapter				DVI and VGA with optional adapter				DVI and VGA				DVI and VGA with optional adapter				

Continue at page 2

Technical Specifications	XT9000-I	XT9200-I	XP9400-I	WE9700-I	WT9000-C	WT9100-C	XT9000-C	XT9200-C	XP9400-C	WE9700-C	WT9100-U	XT9000-U	XT9200-U	XP9400-U	WE9700-U	XT9050-A	XP9400-A	WE9700-A
Operating System	ThinOX V8	ThinOX V8	XPe SP3	WES7 SP1	CE 6.0R2	CE 6.0R2	ThinOX V8	ThinOX V8	XPe SP3	WES7 SP1	CE 6.0R2	ThinOX V8	ThinOX V8	XPe SP3	WES7 SP1	ThinOX V8	XPe SP3	WES7 SP1
RAM Memory / Flash memory	512MB-256MB	512MB-256MB	1GB-2GB	2GB-4GB	256MB-128MB	256MB-128MB	512MB-256MB	512MB-512MB	1GB-2GB	2GB-4GB	256MB-128MB	512MB-256MB	512MB-512MB	1GB-2GB	2GB-4GB	512MB-512MB	1GB-2GB	2GB-4GB
Protocols and resident clients																		
TCP/IP, DNS, DHCP, FTP, SNMP MIB II	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
802.1X Ethernet EAP/PEAP MSCHAPV2 Authentication	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
RDP Client	RDP 6.0*	RDP 6.0*	RDP 7.0	RDP 7.1	RDP 6.0	RDP 6.0	RDP 6.0*	RDP 6.0*	RDP 7.0	RDP 7.1	RDP 6.0	RDP 6.0*	RDP 6.0*	RDP 7.0	RDP 7.1	RDP 6.0*	RDP 7.0	RDP 7.1
Citrix ICA, PN Agent, Citrix XenDesktop Clients	ICA 11.1	ICA 11.1	ICA 12.0	ICA 12.1	ICA 10.0	ICA 10.0	ICA 11.1	ICA 11.1	ICA 12.0	ICA 12.1	ICA 10.0	ICA 11.1	ICA 11.1	ICA 12.0	ICA 12.1	ICA 11.1	ICA 12.0	ICA 12.1
Citrix HDX - MediaStream Server Rendered Media	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Citrix HDX - MediaStream Client Rendered Media	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Citrix HDX Plug & Play (USB redirection) support	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
VMware View Client	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	3.1/RDP	3.1/RDP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	3.1/RDP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP	4.6/RDP/PCoIP
VMware View MMR support	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
USB re-direction client VMware View	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
USB re-direction client Praim (TcE Virtual Desktop)	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Ericom PowerTerm WebConnect Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Leostream Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Provision Networks VAS (Quest software) Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Browser	Firefox 3.0.1	Firefox 3.0.1	IE 7.0	IE 8.0	IE 6.0	IE 6.0	Firefox 3.0.1	Firefox 3.0.1	IE 7.0	IE 8.0	IE 6.0	Firefox 3.0.1	Firefox 3.0.1	IE 7.0	IE 8.0	Firefox 3.0.1	IE 7.0	IE 8.0
Praim TN5250E / 3270 Video e Printer Emulator	•	•	Opt Net2000	OptNet2000	•	•	•	•	•	OptNet2000	•	•	•	•	OptNet2000	•	Opt Net2000	OptNet2000
Praim VT/ASCII Emulator	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Local PDF Viewer	•	PDF 7.0	PDF 7.0	PDF 7.0	•	•	•	PDF 7.0	PDF 7.0	PDF 7.0	•	•	PDF 7.0	PDF 7.0	PDF 7.0	PDF 7.0	PDF 7.0	PDF 7.0
Microsoft .NET Framework	•	•	2.0	2.0-3.0-3.5	•	•	•	2.0	2.0	2.0-3.0-3.5	•	•	2.0	2.0	2.0-3.0-3.5	•	2.0	2.0-3.0-3.5
Media Player, Wordpad	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
E-mail client	•	Thunderbird	Outlook Exp.	•	•	•	•	Thunderbird	Outlook Exp.	•	•	•	Thunderbird	Outlook Exp.	•	Thunderbird	Outlook Exp.	•
JVM	•	SUN 1.6	•	•	•	•	•	SUN 1.6	•	•	•	•	SUN 1.6	•	•	•	•	•
Flash Player	•	Adobe Flash 10	•	•	•	•	•	Adobe Flash 10	•	•	•	•	Adobe Flash 10	•	•	•	•	•
Open Office	•	OpenOffice 3.3	•	•	•	•	•	OpenOffice 3.3	•	•	•	•	OpenOffice 3.3	•	•	•	•	•
Skype local voip Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
NX Nomachine Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
X11 nativo Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Propalms TSE Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
VNC Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Shell script session	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
CUPS printing	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Cisco VPN Client	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
LPD/LPR and RAW	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
User Disk partition	•	•	~ 1GB	~ 1.5GB	•	•	•	50MB	~ 1GB	~ 1.5GB	•	•	50MB	~ 1GB	~ 1.5GB	50MB	~ 1GB	~ 1.5GB
USB re-direction client Praim (TcE Virtual Desktop)	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Supported Operating Systems – Administration																		
Citrix Metaframe 1.7, 1.8, XP, PS Server 4, 4.5	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Citrix XenApp 5.0, 6.0 Citrix XenDesktop 3.0, 4.0	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
VMware View 3.1, 4.0, 4.5	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Microsoft Windows 2000/2003/2008 Terminal Server	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Unix/Linux/AIX	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
IBM AS/400, IBM S/390	•	•	Opt Net2000	Opt	•	•	•	•	•	Opt	•	•	•	•	Opt	•	•	Opt
Central Remote administration via Praim ThinMan	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
ThinMan Enterprise profile manager support	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Remot fw Update / VNC shadowing / Wake On LAN	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Security password and screen saver password	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Options																		
External USB WiFi USB 802.11b/g dongle	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031
Built-in wireless 802.11b/g	80AC00060	80AC00060	80AC00060	80AC00060	80AC00061	80AC00061	80AC00061	80AC00061	80AC00061	80AC00060	80AC00061	80AC00061	80AC00061	80AC00061	80AC00060	80AC00060	80AC00060	80AC00060
Built-in wireless 802.11b/g/n	80AC00063	80AC00063	80AC00063	80AC00063	80AC00062	80AC00062	80AC00062	80AC00062	80AC00062	80AC00063	80AC00062	80AC00062	80AC00062	80AC00062	80AC00063	80AC00063	80AC00063	80AC00063
Built-in smart card reader	--	--	--	--	80AC00065	80AC00065	80AC00065	80AC00065	80AC00065	--	80AC00065	80AC00065	80AC00065	80AC00065	--	--	--	--
PCI adapter with LPT1 + COM2	--	--	--	--	--	--	--	--	--	--	80AC00070	80AC00070	80AC00070	80AC00070	--	--	--	--
Dual monitor adapter from DVI-I to DVI and VGA	--	--	--	--	80EC00019	80EC00019	80EC00019	80EC00019	80EC00019	--	--	--	--	--	--	80EC00019	80EC00019	--
VGA-VGA 40 cm short monitor cable	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--
DVI-VGA 40 cm short monitor cable	80EC00034	80EC00034	80EC00034	80EC00034	80EC00034	80EC00034	80EC00034	80EC00034	80EC00034	80EC00034	--	--	--	--	80EC00034	80EC00034	80EC00034	80EC00034
DVI-DVI 40 cm short monitor cable	80EC00035	80EC00035	80EC00035	80EC00035	80EC00035	80EC00035	80EC00035	80EC00035	80EC00035	80EC00035	--	--	--	--	80EC00035	80EC00035	80EC00035	80EC00035
USB to Parallel cable adapter	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012	80EC00012
Flash disk expansion	--	--	4GB	--	--	--	--	--	4GB	--	--	--	--	4GB	--	--	4GB	--
RAM memory DDR2 expansion	1GB	1GB,2GB	2GB	--	1GB,2GB	1GB,2GB	1GB,2GB	1GB,2GB	2GB	--	1GB,2GB	1GB,2GB	1GB,2GB	2GB	--	1GB,2GB	2GB	--
105 keys PS/2 keyboard with PC standard layout	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001
105 keys PS/2 keyboard with PC/5250 double layout	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002
LCD VESA mounting KIT	80EC00027	80EC00027	80EC00027	80EC00027	80EC00027	80EC00027	80EC00027	80EC00027	80EC00027	80EC00027	--	--	--	--	80EC00027	80EC00027	80EC00027	80EC00027
WALL mount VESA mounting KIT	80EC00026	80EC00026	80EC00026	80EC00026	80EC00026	80EC00026	80EC00026	80EC00026	80EC00026	80EC00026	--	--	--	--	80EC00026	80EC00026	80EC00026	80EC00026
Media streaming codecs Add-On software license	76AC00006	76AC00006	--	--	--	--	76AC00006	76AC00006	--	--	--	76AC00006	76AC00006	--	--	76AC00006	--	--
Technology partners certifications																		
VMware Ready	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Citrix Ready	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Citrix HDX Ready	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•

VMware Ready link: